

Lp отражения от воздуховода								
Lp за счет поворота								
Lp	54	62	64	67	63	58	57	48
<b>B15</b>								
Lp общ.	69	73	74	78	82	81	80	75
Lp шумогл	4	4	6	14	21	29	22	23
Lp за счет расстояния	0,6	0,6	0,3	0,15	0,15	0,15	0,15	0,15
Lp отражения от воздуховода	10	5	2	0	0	0	0	0
Lp за счет поворота								
Lp	54,4	63,4	65,7	63,85	60,85	51,85	57,85	51,85
<b>B16</b>								
Lp общ.	53	62	69	66	62	62	57	48
Lp шумогл								
Lp за счет расстояния								
Lp отражения от воздуховода								
Lp за счет поворота								
Lp	53	62	69	66	62	62	57	48
<b>B17</b>								
Lp общ.	53	62	69	66	62	62	57	48
Lp шумогл								
Lp за счет расстояния								
Lp отражения от воздуховода								
Lp за счет поворота								
Lp	53	62	69	66	62	62	57	48
<b>B18</b>								
Lp общ.	53	62	69	66	62	62	57	48
Lp шумогл								
Lp за счет расстояния								
Lp отражения от воздуховода								
Lp за счет поворота								
Lp	53	62	69	66	62	62	57	48
<b>B19</b>								
Lp общ.	44	47	63	66	67	65	60	48



Lp	35,94	42,9	45,9	36,85	43,8	44,8	43,8	32,8
<b>B24</b>								
Lp общ.	66	69	72	75	76	75	75	69
Lp шумогл	4	4	6	14	21	29	22	23
Lp за счет расстояния	0,6	0,6	0,3	0,15	0,15	0,15	0,15	0,15
Lp отражения от воздуховода	10	5	2	0	0	0	0	0
Lp за счет поворота								
Lp	51,4	59,4	63,7	60,85	54,85	45,85	52,85	45,85

Таблица 8.2

среднегеометрические частоты, Гц	63,0	125,0	250,0	500,0	1000,0	2000,0	4000,0	8000,0
<b>Расчетная точка №1</b>								
Lp П1	61,0	66,0	65,0	51,0	51,0	43,0	48,0	42,0
15log(r/ro)	25,1	25,1	25,1	25,1	25,1	25,1	25,1	25,1
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>27,9</b>	<b>32,9</b>	<b>31,9</b>	<b>17,9</b>	<b>17,9</b>	<b>9,9</b>	<b>14,9</b>	<b>8,9</b>
Lp П2	62,0	68,0	63,0	52,0	50,0	42,0	48,0	42,0
15log(r/ro)	25,1	25,1	25,1	25,1	25,1	25,1	25,1	25,1
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>28,9</b>	<b>34,9</b>	<b>29,9</b>	<b>18,9</b>	<b>16,9</b>	<b>8,9</b>	<b>14,9</b>	<b>8,9</b>
Lp П3	62,0	68,0	63,0	52,0	50,0	42,0	48,0	42,0
15log(r/ro)	25,1	25,1	25,1	25,1	25,1	25,1	25,1	25,1
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>28,9</b>	<b>34,9</b>	<b>29,9</b>	<b>18,9</b>	<b>16,9</b>	<b>8,9</b>	<b>14,9</b>	<b>8,9</b>
Lp П4	45,0	47,0	50,0	41,0	46,0	41,0	43,0	31,0
15log(r/ro)	25,1	25,1	25,1	25,1	25,1	25,1	25,1	25,1
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>11,9</b>	<b>13,9</b>	<b>16,9</b>	<b>7,9</b>	<b>12,9</b>	<b>7,9</b>	<b>9,9</b>	<b>-2,1</b>
Lp П5	47,0	48,0	46,0	38,0	43,0	51,0	44,0	46,0
15log(r/ro)	36,4	36,4	36,4	36,4	36,4	36,4	36,4	36,4
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>2,6</b>	<b>3,6</b>	<b>1,6</b>	<b>-6,4</b>	<b>-1,4</b>	<b>6,6</b>	<b>-0,4</b>	<b>1,6</b>
Lp П6	49,0	51,0	50,0	40,0	41,0	41,0	40,0	36,0
15log(r/ro)	25,1	25,1	25,1	25,1	25,1	25,1	25,1	25,1
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>15,9</b>	<b>17,9</b>	<b>16,9</b>	<b>6,9</b>	<b>7,9</b>	<b>7,9</b>	<b>6,9</b>	<b>2,9</b>
Lp П7	47,0	48,0	46,0	38,0	43,0	51,0	44,0	46,0
15log(r/ro)	36,9	36,9	36,9	36,9	36,9	36,9	36,9	36,9
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>2,1</b>	<b>3,1</b>	<b>1,1</b>	<b>-6,9</b>	<b>-1,9</b>	<b>6,1</b>	<b>-0,9</b>	<b>1,1</b>
Lp П8	48,0	53,0	52,0	39,0	44,0	45,0	44,0	33,0
15log(r/ro)	25,1	25,1	25,1	25,1	25,1	25,1	25,1	25,1
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>14,9</b>	<b>19,9</b>	<b>18,9</b>	<b>5,9</b>	<b>10,9</b>	<b>11,9</b>	<b>10,9</b>	<b>-0,1</b>
Lp П9	62,0	68,0	63,0	52,0	50,0	42,0	48,0	42,0
15log(r/ro)	35,6	35,6	35,6	35,6	35,6	35,6	35,6	35,6
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>18,5</b>	<b>24,5</b>	<b>19,5</b>	<b>8,5</b>	<b>6,5</b>	<b>-1,5</b>	<b>4,5</b>	<b>-1,5</b>
Lp П10	61,0	66,0	65,0	51,0	51,0	43,0	48,0	42,0
15log(r/ro)	35,6	35,6	35,6	35,6	35,6	35,6	35,6	35,6
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>17,5</b>	<b>22,5</b>	<b>21,5</b>	<b>7,5</b>	<b>7,5</b>	<b>-0,5</b>	<b>4,5</b>	<b>-1,5</b>
Lp П11	61,0	66,0	65,0	51,0	51,0	43,0	48,0	42,0
15log(r/ro)	34,0	34,0	34,0	34,0	34,0	34,0	34,0	34,0
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>19,0</b>	<b>24,0</b>	<b>23,0</b>	<b>9,0</b>	<b>9,0</b>	<b>1,0</b>	<b>6,0</b>	<b>0,0</b>
Lp П12	61,0	66,0	65,0	51,0	51,0	43,0	48,0	42,0
15log(r/ro)	34,0	34,0	34,0	34,0	34,0	34,0	34,0	34,0
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>19,0</b>	<b>24,0</b>	<b>23,0</b>	<b>9,0</b>	<b>9,0</b>	<b>1,0</b>	<b>6,0</b>	<b>0,0</b>
Lp П13	45,0	47,0	50,0	41,0	46,0	41,0	43,0	31,0

15log(r/ro)	34,0	34,0	34,0	34,0	34,0	34,0	34,0	34,0
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>3,0</b>	<b>5,0</b>	<b>8,0</b>	<b>-1,0</b>	<b>4,0</b>	<b>-1,0</b>	<b>1,0</b>	<b>-11,0</b>
Lp Π14	47,0	50,0	46,0	37,0	41,0	49,0	46,0	40,0
15log(r/ro)	25,1	25,1	25,1	25,1	25,1	25,1	25,1	25,1
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>13,9</b>	<b>16,9</b>	<b>12,9</b>	<b>3,9</b>	<b>7,9</b>	<b>15,9</b>	<b>12,9</b>	<b>6,9</b>
Lp B1	51,4	69,4	63,7	58,9	54,9	45,9	52,9	45,9
15log(r/ro)	22,4	22,4	22,4	22,4	22,4	22,4	22,4	22,4
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>21,0</b>	<b>39,0</b>	<b>33,3</b>	<b>28,5</b>	<b>24,5</b>	<b>15,5</b>	<b>22,5</b>	<b>15,5</b>
Lp B2	56,0	53,9	52,9	36,9	48,9	52,9	51,9	50,9
15log(r/ro)	25,1	25,1	25,1	25,1	25,1	25,1	25,1	25,1
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>22,9</b>	<b>20,9</b>	<b>19,9</b>	<b>3,8</b>	<b>15,8</b>	<b>19,8</b>	<b>18,8</b>	<b>17,8</b>
Lp B3	37,9	41,9	44,9	38,9	43,8	46,8	44,8	41,8
15log(r/ro)	25,1	25,1	25,1	25,1	25,1	25,1	25,1	25,1
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>4,9</b>	<b>8,8</b>	<b>11,8</b>	<b>5,8</b>	<b>10,7</b>	<b>13,7</b>	<b>11,7</b>	<b>8,7</b>
Lp B4	37,9	41,9	44,9	38,9	43,8	46,8	44,8	41,8
15log(r/ro)	27,1	27,1	27,1	27,1	27,1	27,1	27,1	27,1
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>2,9</b>	<b>6,8</b>	<b>9,8</b>	<b>3,8</b>	<b>8,7</b>	<b>11,7</b>	<b>9,7</b>	<b>6,7</b>
Lp B5	54,4	62,4	65,7	61,9	58,9	49,9	55,9	49,9
15log(r/ro)	25,1	25,1	25,1	25,1	25,1	25,1	25,1	25,1
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>21,3</b>	<b>29,3</b>	<b>32,6</b>	<b>28,8</b>	<b>25,8</b>	<b>16,8</b>	<b>22,8</b>	<b>16,8</b>
Lp B6	54,4	62,4	65,7	61,9	58,9	49,9	55,9	49,9
15log(r/ro)	25,1	25,1	25,1	25,1	25,1	25,1	25,1	25,1
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>21,3</b>	<b>29,3</b>	<b>32,6</b>	<b>28,8</b>	<b>25,8</b>	<b>16,8</b>	<b>22,8</b>	<b>16,8</b>
Lp B7	37,9	41,9	45,9	39,9	45,8	40,8	42,8	30,8
15log(r/ro)	22,4	22,4	22,4	22,4	22,4	22,4	22,4	22,4
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>7,6</b>	<b>11,5</b>	<b>15,5</b>	<b>9,5</b>	<b>15,4</b>	<b>10,4</b>	<b>12,4</b>	<b>0,4</b>
Lp B8	35,9	51,9	60,9	64,9	66,8	63,8	61,8	46,8
15log(r/ro)	22,4	22,4	22,4	22,4	22,4	22,4	22,4	22,4
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>5,6</b>	<b>21,5</b>	<b>30,5</b>	<b>34,5</b>	<b>36,4</b>	<b>33,4</b>	<b>31,4</b>	<b>16,4</b>
Lp B9	54,4	62,4	65,7	61,9	58,9	49,9	55,9	49,9
15log(r/ro)	25,1	25,1	25,1	25,1	25,1	25,1	25,1	25,1
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>21,3</b>	<b>29,3</b>	<b>32,6</b>	<b>28,8</b>	<b>25,8</b>	<b>16,8</b>	<b>22,8</b>	<b>16,8</b>
Lp B10	51,4	59,4	63,7	60,9	52,9	41,9	46,9	39,9
15log(r/ro)	25,1	25,1	25,1	25,1	25,1	25,1	25,1	25,1
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>18,3</b>	<b>26,3</b>	<b>30,6</b>	<b>27,8</b>	<b>19,8</b>	<b>8,8</b>	<b>13,8</b>	<b>6,8</b>
Lp B11	53,0	62,0	69,0	66,0	62,0	62,0	57,0	48,0
15log(r/ro)	23,9	23,9	23,9	23,9	23,9	23,9	23,9	23,9
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>21,1</b>	<b>30,1</b>	<b>37,1</b>	<b>34,1</b>	<b>30,1</b>	<b>30,1</b>	<b>25,1</b>	<b>16,1</b>
Lp B12	53,0	62,0	69,0	66,0	62,0	62,0	57,0	48,0
15log(r/ro)	25,1	25,1	25,1	25,1	25,1	25,1	25,1	25,1
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>19,9</b>	<b>28,9</b>	<b>35,9</b>	<b>32,9</b>	<b>28,9</b>	<b>28,9</b>	<b>23,9</b>	<b>14,9</b>
Lp B13	54,0	62,0	64,0	67,0	63,0	58,0	57,0	48,0

15log(r/ro)	25,1	25,1	25,1	25,1	25,1	25,1	25,1	25,1
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>20,9</b>	<b>28,9</b>	<b>30,9</b>	<b>33,9</b>	<b>29,9</b>	<b>24,9</b>	<b>23,9</b>	<b>14,9</b>
Lp B14	54,0	62,0	64,0	67,0	63,0	58,0	57,0	48,0
15log(r/ro)	23,9	23,9	23,9	23,9	23,9	23,9	23,9	23,9
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>22,1</b>	<b>30,1</b>	<b>32,1</b>	<b>35,1</b>	<b>31,1</b>	<b>26,1</b>	<b>25,1</b>	<b>16,1</b>
Lp B15	54,4	63,4	65,7	63,9	60,9	51,9	57,9	51,9
15log(r/ro)	22,4	22,4	22,4	22,4	22,4	22,4	22,4	22,4
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>24,0</b>	<b>33,0</b>	<b>35,3</b>	<b>33,5</b>	<b>30,5</b>	<b>21,5</b>	<b>27,5</b>	<b>21,5</b>
Lp B16	53,0	62,0	69,0	66,0	62,0	62,0	57,0	48,0
15log(r/ro)	23,9	23,9	23,9	23,9	23,9	23,9	23,9	23,9
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>21,1</b>	<b>30,1</b>	<b>37,1</b>	<b>34,1</b>	<b>30,1</b>	<b>30,1</b>	<b>25,1</b>	<b>16,1</b>
Lp B17	53,0	62,0	69,0	66,0	62,0	62,0	57,0	48,0
15log(r/ro)	23,9	23,9	23,9	23,9	23,9	23,9	23,9	23,9
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>21,1</b>	<b>30,1</b>	<b>37,1</b>	<b>34,1</b>	<b>30,1</b>	<b>30,1</b>	<b>25,1</b>	<b>16,1</b>
Lp B18	53,0	62,0	69,0	66,0	62,0	62,0	57,0	48,0
15log(r/ro)	23,9	23,9	23,9	23,9	23,9	23,9	23,9	23,9
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>21,1</b>	<b>30,1</b>	<b>37,1</b>	<b>34,1</b>	<b>30,1</b>	<b>30,1</b>	<b>25,1</b>	<b>16,1</b>
Lp B19	44,0	47,0	63,0	66,0	67,0	65,0	60,0	48,0
15log(r/ro)	25,1	25,1	25,1	25,1	25,1	25,1	25,1	25,1
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>10,9</b>	<b>13,9</b>	<b>29,9</b>	<b>32,9</b>	<b>33,9</b>	<b>31,9</b>	<b>26,9</b>	<b>14,9</b>
Lp B20	55,9	53,9	52,9	36,9	48,8	52,8	51,8	50,8
15log(r/ro)	25,1	25,1	25,1	25,1	25,1	25,1	25,1	25,1
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>22,9</b>	<b>20,8</b>	<b>19,8</b>	<b>3,8</b>	<b>15,7</b>	<b>19,7</b>	<b>18,7</b>	<b>17,7</b>
Lp B21	55,9	53,9	52,9	36,9	48,8	52,8	51,8	50,8
15log(r/ro)	27,1	27,1	27,1	27,1	27,1	27,1	27,1	27,1
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>20,9</b>	<b>18,8</b>	<b>17,8</b>	<b>1,8</b>	<b>13,7</b>	<b>17,7</b>	<b>16,7</b>	<b>15,7</b>
Lp B22	56,9	55,9	53,9	36,9	48,8	52,8	51,8	50,8
15log(r/ro)	27,1	27,1	27,1	27,1	27,1	27,1	27,1	27,1
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>21,9</b>	<b>20,8</b>	<b>18,8</b>	<b>1,8</b>	<b>13,7</b>	<b>17,7</b>	<b>16,7</b>	<b>15,7</b>
Lp B23	35,9	42,9	45,9	36,9	43,8	44,8	43,8	32,8
15log(r/ro)	27,1	27,1	27,1	27,1	27,1	27,1	27,1	27,1
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>0,9</b>	<b>7,8</b>	<b>10,8</b>	<b>1,8</b>	<b>8,7</b>	<b>9,7</b>	<b>8,7</b>	<b>-2,3</b>
Lp B24	51,4	59,4	63,7	60,9	54,9	45,9	52,9	45,9
15log(r/ro)	22,4	22,4	22,4	22,4	22,4	22,4	22,4	22,4
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>21,0</b>	<b>29,0</b>	<b>33,3</b>	<b>30,5</b>	<b>24,5</b>	<b>15,5</b>	<b>22,5</b>	<b>15,5</b>
<b>Лсумм. В расчетной точке №1</b>								
	37,1	44,8	46,9	44,8	42,4	40,1	37,7	29,7
Нормы в дневное время	70,0	61,0	54,0	49,0	45,0	42,0	40,0	39,0
Превышение норм	-32,9	-16,2	-7,1	-4,2	-2,6	-1,9	-2,3	-9,3

Таблица 8.3

	63,0	125,0	250,0	500,0	1000,0	2000,0	4000,0	8000,0
<b>Расчетная точка №2</b>								
Lp П1	61,0	66,0	65,0	51,0	51,0	43,0	48,0	42,0
15log(r/ro)	28,3	28,3	28,3	28,3	28,3	28,3	28,3	28,3
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>24,7</b>	<b>29,7</b>	<b>28,7</b>	<b>14,7</b>	<b>14,7</b>	<b>6,7</b>	<b>11,7</b>	<b>5,7</b>
Lp П2	62,0	68,0	63,0	52,0	50,0	42,0	48,0	42,0
15log(r/ro)	28,3	28,3	28,3	28,3	28,3	28,3	28,3	28,3
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>25,7</b>	<b>31,7</b>	<b>26,7</b>	<b>15,7</b>	<b>13,7</b>	<b>5,7</b>	<b>11,7</b>	<b>5,7</b>
Lp П3	62,0	68,0	63,0	52,0	50,0	42,0	48,0	42,0
15log(r/ro)	28,3	28,3	28,3	28,3	28,3	28,3	28,3	28,3
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>25,7</b>	<b>31,7</b>	<b>26,7</b>	<b>15,7</b>	<b>13,7</b>	<b>5,7</b>	<b>11,7</b>	<b>5,7</b>
Lp П4	45,0	47,0	50,0	41,0	46,0	41,0	43,0	31,0
15log(r/ro)	28,3	28,3	28,3	28,3	28,3	28,3	28,3	28,3
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>8,7</b>	<b>10,7</b>	<b>13,7</b>	<b>4,7</b>	<b>9,7</b>	<b>4,7</b>	<b>6,7</b>	<b>-5,3</b>
Lp П5	47,0	48,0	46,0	38,0	43,0	51,0	44,0	46,0
15log(r/ro)	36,4	36,4	36,4	36,4	36,4	36,4	36,4	36,4
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>2,6</b>	<b>3,6</b>	<b>1,6</b>	<b>-6,4</b>	<b>-1,4</b>	<b>6,6</b>	<b>-0,4</b>	<b>1,6</b>
Lp П6	49,0	51,0	50,0	40,0	41,0	41,0	40,0	36,0
15log(r/ro)	28,3	28,3	28,3	28,3	28,3	28,3	28,3	28,3
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>12,7</b>	<b>14,7</b>	<b>13,7</b>	<b>3,7</b>	<b>4,7</b>	<b>4,7</b>	<b>3,7</b>	<b>-0,3</b>
Lp П7	47,0	48,0	46,0	38,0	43,0	51,0	44,0	46,0
15log(r/ro)	36,9	36,9	36,9	36,9	36,9	36,9	36,9	36,9
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>2,1</b>	<b>3,1</b>	<b>1,1</b>	<b>-6,9</b>	<b>-1,9</b>	<b>6,1</b>	<b>-0,9</b>	<b>1,1</b>
Lp П8	48,0	53,0	52,0	39,0	44,0	45,0	44,0	33,0
15log(r/ro)	28,3	28,3	28,3	28,3	28,3	28,3	28,3	28,3
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>11,7</b>	<b>16,7</b>	<b>15,7</b>	<b>2,7</b>	<b>7,7</b>	<b>8,7</b>	<b>7,7</b>	<b>-3,3</b>
Lp П9	62,0	68,0	63,0	52,0	50,0	42,0	48,0	42,0
15log(r/ro)	35,6	35,6	35,6	35,6	35,6	35,6	35,6	35,6
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>18,5</b>	<b>24,5</b>	<b>19,5</b>	<b>8,5</b>	<b>6,5</b>	<b>-1,5</b>	<b>4,5</b>	<b>-1,5</b>
Lp П10	61,0	66,0	65,0	51,0	51,0	43,0	48,0	42,0
15log(r/ro)	35,6	35,6	35,6	35,6	35,6	35,6	35,6	35,6
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>17,5</b>	<b>22,5</b>	<b>21,5</b>	<b>7,5</b>	<b>7,5</b>	<b>-0,5</b>	<b>4,5</b>	<b>-1,5</b>
Lp П11	61,0	66,0	65,0	51,0	51,0	43,0	48,0	42,0
15log(r/ro)	34,0	34,0	34,0	34,0	34,0	34,0	34,0	34,0
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>19,0</b>	<b>24,0</b>	<b>23,0</b>	<b>9,0</b>	<b>9,0</b>	<b>1,0</b>	<b>6,0</b>	<b>0,0</b>
Lp П12	61,0	66,0	65,0	51,0	51,0	43,0	48,0	42,0
15log(r/ro)	34,0	34,0	34,0	34,0	34,0	34,0	34,0	34,0
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>19,0</b>	<b>24,0</b>	<b>23,0</b>	<b>9,0</b>	<b>9,0</b>	<b>1,0</b>	<b>6,0</b>	<b>0,0</b>
Lp П13	45,0	47,0	50,0	41,0	46,0	41,0	43,0	31,0
15log(r/ro)	34,0	34,0	34,0	34,0	34,0	34,0	34,0	34,0
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>3,0</b>	<b>5,0</b>	<b>8,0</b>	<b>-1,0</b>	<b>4,0</b>	<b>-1,0</b>	<b>1,0</b>	<b>-11,0</b>

Lp П14	47,0	50,0	46,0	37,0	41,0	49,0	46,0	40,0
15log(r/ro)	28,3	28,3	28,3	28,3	28,3	28,3	28,3	28,3
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>10,7</b>	<b>13,7</b>	<b>9,7</b>	<b>0,7</b>	<b>4,7</b>	<b>12,7</b>	<b>9,7</b>	<b>3,7</b>
Lp B1	51,4	69,4	63,7	58,9	54,9	45,9	52,9	45,9
15log(r/ro)	26,7	26,7	26,7	26,7	26,7	26,7	26,7	26,7
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>16,7</b>	<b>34,7</b>	<b>29,0</b>	<b>24,2</b>	<b>20,2</b>	<b>11,2</b>	<b>18,2</b>	<b>11,2</b>
Lp B2	56,0	53,9	52,9	36,9	48,9	52,9	51,9	50,9
15log(r/ro)	28,3	28,3	28,3	28,3	28,3	28,3	28,3	28,3
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>19,7</b>	<b>17,7</b>	<b>16,7</b>	<b>0,6</b>	<b>12,6</b>	<b>16,6</b>	<b>15,6</b>	<b>14,6</b>
Lp B3	37,9	41,9	44,9	38,9	43,8	46,8	44,8	41,8
15log(r/ro)	23,9	23,9	23,9	23,9	23,9	23,9	23,9	23,9
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>6,1</b>	<b>10,0</b>	<b>13,0</b>	<b>7,0</b>	<b>11,9</b>	<b>14,9</b>	<b>12,9</b>	<b>9,9</b>
Lp B4	37,9	41,9	44,9	38,9	43,8	46,8	44,8	41,8
15log(r/ro)	26,8	26,8	26,8	26,8	26,8	26,8	26,8	26,8
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>3,2</b>	<b>7,1</b>	<b>10,1</b>	<b>4,1</b>	<b>9,0</b>	<b>12,0</b>	<b>10,0</b>	<b>7,0</b>
Lp B5	54,4	62,4	65,7	61,9	58,9	49,9	55,9	49,9
15log(r/ro)	28,3	28,3	28,3	28,3	28,3	28,3	28,3	28,3
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>18,1</b>	<b>26,1</b>	<b>29,4</b>	<b>25,6</b>	<b>22,6</b>	<b>13,6</b>	<b>19,6</b>	<b>13,6</b>
Lp B6	54,4	62,4	65,7	61,9	58,9	49,9	55,9	49,9
15log(r/ro)	28,3	28,3	28,3	28,3	28,3	28,3	28,3	28,3
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>18,1</b>	<b>26,1</b>	<b>29,4</b>	<b>25,6</b>	<b>22,6</b>	<b>13,6</b>	<b>19,6</b>	<b>13,6</b>
Lp B7	37,9	41,9	45,9	39,9	45,8	40,8	42,8	30,8
15log(r/ro)	26,7	26,7	26,7	26,7	26,7	26,7	26,7	26,7
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>3,3</b>	<b>7,2</b>	<b>11,2</b>	<b>5,2</b>	<b>11,1</b>	<b>6,1</b>	<b>8,1</b>	<b>-3,9</b>
Lp B8	35,9	51,9	60,9	64,9	66,8	63,8	61,8	46,8
15log(r/ro)	26,7	26,7	26,7	26,7	26,7	26,7	26,7	26,7
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>1,3</b>	<b>17,2</b>	<b>26,2</b>	<b>30,2</b>	<b>32,1</b>	<b>29,1</b>	<b>27,1</b>	<b>12,1</b>
Lp B9	54,4	62,4	65,7	61,9	58,9	49,9	55,9	49,9
15log(r/ro)	28,3	28,3	28,3	28,3	28,3	28,3	28,3	28,3
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>18,1</b>	<b>26,1</b>	<b>29,4</b>	<b>25,6</b>	<b>22,6</b>	<b>13,6</b>	<b>19,6</b>	<b>13,6</b>
Lp B10	51,4	59,4	63,7	60,9	52,9	41,9	46,9	39,9
15log(r/ro)	28,3	28,3	28,3	28,3	28,3	28,3	28,3	28,3
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>15,1</b>	<b>23,1</b>	<b>27,4</b>	<b>24,6</b>	<b>16,6</b>	<b>5,6</b>	<b>10,6</b>	<b>3,6</b>
Lp B11	53,0	62,0	69,0	66,0	62,0	62,0	57,0	48,0
15log(r/ro)	24,8	24,8	24,8	24,8	24,8	24,8	24,8	24,8
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>20,2</b>	<b>29,2</b>	<b>36,2</b>	<b>33,2</b>	<b>29,2</b>	<b>29,2</b>	<b>24,2</b>	<b>15,2</b>
Lp B12	53,0	62,0	69,0	66,0	62,0	62,0	57,0	48,0
15log(r/ro)	23,9	23,9	23,9	23,9	23,9	23,9	23,9	23,9
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>21,1</b>	<b>30,1</b>	<b>37,1</b>	<b>34,1</b>	<b>30,1</b>	<b>30,1</b>	<b>25,1</b>	<b>16,1</b>
Lp B13	54,0	62,0	64,0	67,0	63,0	58,0	57,0	48,0
15log(r/ro)	28,3	28,3	28,3	28,3	28,3	28,3	28,3	28,3
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>17,7</b>	<b>25,7</b>	<b>27,7</b>	<b>30,7</b>	<b>26,7</b>	<b>21,7</b>	<b>20,7</b>	<b>11,7</b>



Lp B14	54,0	62,0	64,0	67,0	63,0	58,0	57,0	48,0
15log(r/ro)	24,8	24,8	24,8	24,8	24,8	24,8	24,8	24,8
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>21,2</b>	<b>29,2</b>	<b>31,2</b>	<b>34,2</b>	<b>30,2</b>	<b>25,2</b>	<b>24,2</b>	<b>15,2</b>
Lp B15	54,4	63,4	65,7	63,9	60,9	51,9	57,9	51,9
15log(r/ro)	26,7	26,7	26,7	26,7	26,7	26,7	26,7	26,7
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>19,7</b>	<b>28,7</b>	<b>31,0</b>	<b>29,2</b>	<b>26,2</b>	<b>17,2</b>	<b>23,2</b>	<b>17,2</b>
Lp B16	53,0	62,0	69,0	66,0	62,0	62,0	57,0	48,0
15log(r/ro)	24,8	24,8	24,8	24,8	24,8	24,8	24,8	24,8
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>20,2</b>	<b>29,2</b>	<b>36,2</b>	<b>33,2</b>	<b>29,2</b>	<b>29,2</b>	<b>24,2</b>	<b>15,2</b>
Lp B17	53,0	62,0	69,0	66,0	62,0	62,0	57,0	48,0
15log(r/ro)	24,8	24,8	24,8	24,8	24,8	24,8	24,8	24,8
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>20,2</b>	<b>29,2</b>	<b>36,2</b>	<b>33,2</b>	<b>29,2</b>	<b>29,2</b>	<b>24,2</b>	<b>15,2</b>
Lp B18	53,0	62,0	69,0	66,0	62,0	62,0	57,0	48,0
15log(r/ro)	24,8	24,8	24,8	24,8	24,8	24,8	24,8	24,8
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>20,2</b>	<b>29,2</b>	<b>36,2</b>	<b>33,2</b>	<b>29,2</b>	<b>29,2</b>	<b>24,2</b>	<b>15,2</b>
Lp B19	44,0	47,0	63,0	66,0	67,0	65,0	60,0	48,0
15log(r/ro)	23,9	23,9	23,9	23,9	23,9	23,9	23,9	23,9
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>12,1</b>	<b>15,1</b>	<b>31,1</b>	<b>34,1</b>	<b>35,1</b>	<b>33,1</b>	<b>28,1</b>	<b>16,1</b>
Lp B20	55,9	53,9	52,9	36,9	48,8	52,8	51,8	50,8
15log(r/ro)	23,9	23,9	23,9	23,9	23,9	23,9	23,9	23,9
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>24,1</b>	<b>22,0</b>	<b>21,0</b>	<b>5,0</b>	<b>16,9</b>	<b>20,9</b>	<b>19,9</b>	<b>18,9</b>
Lp B21	55,9	53,9	52,9	36,9	48,8	52,8	51,8	50,8
15log(r/ro)	26,8	26,8	26,8	26,8	26,8	26,8	26,8	26,8
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>21,2</b>	<b>19,1</b>	<b>18,1</b>	<b>2,1</b>	<b>14,0</b>	<b>18,0</b>	<b>17,0</b>	<b>16,0</b>
Lp B22	56,9	55,9	53,9	36,9	48,8	52,8	51,8	50,8
15log(r/ro)	26,8	26,8	26,8	26,8	26,8	26,8	26,8	26,8
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>22,2</b>	<b>21,1</b>	<b>19,1</b>	<b>2,1</b>	<b>14,0</b>	<b>18,0</b>	<b>17,0</b>	<b>16,0</b>
Lp B23	35,9	42,9	45,9	36,9	43,8	44,8	43,8	32,8
15log(r/ro)	26,8	26,8	26,8	26,8	26,8	26,8	26,8	26,8
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>1,2</b>	<b>8,1</b>	<b>11,1</b>	<b>2,1</b>	<b>9,0</b>	<b>10,0</b>	<b>9,0</b>	<b>-2,0</b>
Lp B24	51,4	59,4	63,7	60,9	54,9	45,9	52,9	45,9
15log(r/ro)	26,7	26,7	26,7	26,7	26,7	26,7	26,7	26,7
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>16,7</b>	<b>24,7</b>	<b>29,0</b>	<b>26,2</b>	<b>20,2</b>	<b>11,2</b>	<b>18,2</b>	<b>11,2</b>
<b>Лсумм. В расчетной точке №2</b>								
	35,1	42,2	45,4	43,3	40,9	39,2	35,9	28,1
Нормы в дневное время	70,0	61,0	54,0	49,0	45,0	42,0	40,0	39,0
Превышение норм	-34,9	-18,8	-8,6	-5,7	-4,1	-2,8	-4,1	-10,9

Таблица 8.4

	63,0	125,0	250,0	500,0	1000,0	2000,0	4000,0	8000,0
<b>Расчетная точка №3</b>								
Lp П1	61,0	66,0	65,0	51,0	51,0	43,0	48,0	42,0
15log(r/ro)	27,1	27,1	27,1	27,1	27,1	27,1	27,1	27,1
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>25,9</b>	<b>30,9</b>	<b>29,9</b>	<b>15,9</b>	<b>15,9</b>	<b>7,9</b>	<b>12,9</b>	<b>6,9</b>
Lp П2	62,0	68,0	63,0	52,0	50,0	42,0	48,0	42,0
15log(r/ro)	27,1	27,1	27,1	27,1	27,1	27,1	27,1	27,1
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>26,9</b>	<b>32,9</b>	<b>27,9</b>	<b>16,9</b>	<b>14,9</b>	<b>6,9</b>	<b>12,9</b>	<b>6,9</b>
Lp П3	62,0	68,0	63,0	52,0	50,0	42,0	48,0	42,0
15log(r/ro)	27,1	27,1	27,1	27,1	27,1	27,1	27,1	27,1
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>26,9</b>	<b>32,9</b>	<b>27,9</b>	<b>16,9</b>	<b>14,9</b>	<b>6,9</b>	<b>12,9</b>	<b>6,9</b>
Lp П4	45,0	47,0	50,0	41,0	46,0	41,0	43,0	31,0
15log(r/ro)	27,1	27,1	27,1	27,1	27,1	27,1	27,1	27,1
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>9,9</b>	<b>11,9</b>	<b>14,9</b>	<b>5,9</b>	<b>10,9</b>	<b>5,9</b>	<b>7,9</b>	<b>-4,1</b>
Lp П5	47,0	48,0	46,0	38,0	43,0	51,0	44,0	46,0
15log(r/ro)	23,0	23,0	23,0	23,0	23,0	23,0	23,0	23,0
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>16,0</b>	<b>17,0</b>	<b>15,0</b>	<b>7,0</b>	<b>12,0</b>	<b>20,0</b>	<b>13,0</b>	<b>15,0</b>
Lp П6	49,0	51,0	50,0	40,0	41,0	41,0	40,0	36,0
15log(r/ro)	27,1	27,1	27,1	27,1	27,1	27,1	27,1	27,1
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>13,9</b>	<b>15,9</b>	<b>14,9</b>	<b>4,9</b>	<b>5,9</b>	<b>5,9</b>	<b>4,9</b>	<b>0,9</b>
Lp П7	47,0	48,0	46,0	38,0	43,0	51,0	44,0	46,0
15log(r/ro)	23,0	23,0	23,0	23,0	23,0	23,0	23,0	23,0
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>16,0</b>	<b>17,0</b>	<b>15,0</b>	<b>7,0</b>	<b>12,0</b>	<b>20,0</b>	<b>13,0</b>	<b>15,0</b>
Lp П8	48,0	53,0	52,0	39,0	44,0	45,0	44,0	33,0
15log(r/ro)	27,1	27,1	27,1	27,1	27,1	27,1	27,1	27,1
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>12,9</b>	<b>17,9</b>	<b>16,9</b>	<b>3,9</b>	<b>8,9</b>	<b>9,9</b>	<b>8,9</b>	<b>-2,1</b>
Lp П9	62,0	68,0	63,0	52,0	50,0	42,0	48,0	42,0
15log(r/ro)	23,0	23,0	23,0	23,0	23,0	23,0	23,0	23,0
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>31,0</b>	<b>37,0</b>	<b>32,0</b>	<b>21,0</b>	<b>19,0</b>	<b>11,0</b>	<b>17,0</b>	<b>11,0</b>
Lp П10	61,0	66,0	65,0	51,0	51,0	43,0	48,0	42,0
15log(r/ro)	23,0	23,0	23,0	23,0	23,0	23,0	23,0	23,0
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>30,0</b>	<b>35,0</b>	<b>34,0</b>	<b>20,0</b>	<b>20,0</b>	<b>12,0</b>	<b>17,0</b>	<b>11,0</b>
Lp П11	61,0	66,0	65,0	51,0	51,0	43,0	48,0	42,0
15log(r/ro)	23,0	23,0	23,0	23,0	23,0	23,0	23,0	23,0
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>30,0</b>	<b>35,0</b>	<b>34,0</b>	<b>20,0</b>	<b>20,0</b>	<b>12,0</b>	<b>17,0</b>	<b>11,0</b>
Lp П12	61,0	66,0	65,0	51,0	51,0	43,0	48,0	42,0
15log(r/ro)	23,0	23,0	23,0	23,0	23,0	23,0	23,0	23,0
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>30,0</b>	<b>35,0</b>	<b>34,0</b>	<b>20,0</b>	<b>20,0</b>	<b>12,0</b>	<b>17,0</b>	<b>11,0</b>
Lp П13	45,0	47,0	50,0	41,0	46,0	41,0	43,0	31,0
15log(r/ro)	23,0	23,0	23,0	23,0	23,0	23,0	23,0	23,0
10logΩ	8,0	8,0	8,0	8,0	8,0	8,0	8,0	8,0
<b>L</b>	<b>14,0</b>	<b>16,0</b>	<b>19,0</b>	<b>10,0</b>	<b>15,0</b>	<b>10,0</b>	<b>12,0</b>	<b>0,0</b>